

AT COMMAND MODE

TCP Client Example

```
COM1:115200baud - Tera Term VT
File Edit Setup Control Window Help

AT Command Ready
AT+JOIN_PROFILE=wadelee,03 79,3
ASSOCIATED
OK
AT+SET_TCP_PROFILE=1,192.168.1.2:2000
OK
AT+SET_TCP_CONNECT=1,1
CONNECTED
OK
AT+GET_TCP_CONNECT=1
CONNECTED
OK
AT+SET_TCP_DATA=1,5,3132333435
OK
AT+GET_TCP_DATA=1
TCP READ:1,6,414243444546
AT+GET_TCP_DATA=1
TCP READ:1,0
AT+SET_TCP_DATA=1,5,3132333435
OK
AT+SET_TCP_CONNECT=1,0
OK
```

系統Ready

加入無線網路
SSID,PWD
加密方式

第一條連線
IP:192.168.1.2
Port:2000

第一條連線啟動

檢查第一條連線狀態

寫入資料給第一條連線
長度5 Bytes
0x31 0x32 0x33 0x34 0x35

第一條連線讀取資料
有讀到6 Bytes
0x41 0x42 0x43 0x44 0x45 0x46

第一條連線讀取資料
回傳長度 0

第一條連線寫入資料
長度 5 Bytes
0x31 0x32 0x33 0x34 0x35

結速第一條連線